



Default DMX Patch

(Last updated 12/07/24 by MH)

There are labels on each fixture with its default DMX address. Please do not readdress theatre-owned equipment without the prior permission of the Management.

Houselights and dimmers are on Universe 1 by default and all DMX socket outlets around stage are Universe 2 by default.

All DMX is fully patchable via an XLR5 panel in the Patchbay.

ETC Source Four Series 2 Lustr x30	108 115 122 129 136 143 150
Use 7 channel 'HSIC Strobe Fan' mode	157 164 171 178 185 192 199
	206 213 220 227 234 241 248
	255 262 269 276 283 290 297
	304 311

ETC ColorSource PAR x20	320 325 330 335 340 345 350
Use 5 channel '5ch' mode	355 360 365 370 375 380 385
	390 395 400 405 410 415

Altman SpectraCyc 200 RGBA x7	420 430 440 450
Use 10 channel '608' mode	460 470 480

Robert Juliet Roxie Followspots	490 495
Use 5 channel 'followspot' mode	

Auditorium Houselights	500
-------------------------------	------------

Auditorium Secondaries	501
-------------------------------	------------

JEM Smoke machine	501
Single 'fog' channel	

Atomic 3000 Strobe	502
Use 4 channel mode	

JEM Hazer Pro	506
See separate 'Hazer Pro' guide for DMX instructions	